

TANE VIDEO-330 CCTV TESTER

The TANE VIDEO-330 tests the camera-video, PTZ function and UTP cable status.

Easy to use on-screen displays identify problems quickly and efficiently.



Model	TANE VIDEO-330	
Video Test Function	Signal Mode	NTSC/PAL automatically suitable
	Display	2.5 inch LCD screen, 960×240 resolution
	Video Input	1 channel BNC
	Video Output	1 channel BNC
	Adjustable	Brightness adjustable
PTZ Control and Test Function	Communication	RS232, RS422 simplex and RS485
	Protocol	Include more than 20 kinds of protocols or customized
	Baud Rate	2400, 4800, 9600, 19200
Multi-meter Function	DC Voltage Test	Max: 1000V, Precision:0.1mV
	AC Voltage Test	Max: 750V, Precision:0.1mV
	Resistance Test	Max: 40mΩ, Precision:0.1mΩ
Power to Camera	Voltage	DC 12V
	Working Time	4-5 Hours to normal camera
	Max Current	260 mA
Other Functions	Video analyzing	Video signal attenuation analyzing
	UTP Cable Test	Test UTP cable connection state
	Signal Generating	Output 1 channel video signal for testing monitor
	RS485 Data Test	Test the RS485 data sent from controlling device
	OSD Menu	English OSD menu
	Keyboard	New design with number buttons, easy to operation
Power and Battery	Power Adapter	DC 5V
	Battery	2800 mAh Lithium battery inside
	Rechargeable	5 hours recharging time
	Low Consumption	Sleeping mode, display battery power state
	Working Time	8-10 hours
Others	Work Temperature	-22°F~ +158°F
	Work Humidity	30%~90%
	Dimension	6.5"H × 3.5"W × 1.9"D
	Weight	11.8 oz

BNC CCTV Connectors



2-PC. BNC PLUG W/3 FERRULES
TN5088-2X
[RG-58,59,59TFE,6]



RCA FEMALE TO BNC MALE
TN50AD515



TWIST-ON RIGHT ANGLE PLUG
TN50RA2
[RG-59 & RG-62]



BNC JACK TO JACK BARREL
TN50AD555




TWIST-ON BNC PLUG
TN50UG882
[RG-59 & RG-62]



BNC RIGHT ANGLE PLUG TO JACK
TN50AD503




TWIST-ON RIGHT ANGLE PLUG
TN50RA5
[RG-6]



BNC T CONNECTOR PLUG TO JACK
TN50AD505




TWIST-ON BNC PLUG
TN50UG885
[RG-6]



2-PC RIGHT ANGLE PLUG W/3 FERRULES
TN50R-2X
[RG-58,59,59TFE,6]



"F" FEMALE-BNC MALE
TN50AD516



BNC JACK T CONNECTOR
TN50AD506



Female BNC - Twist on RG 59
TN-C5030RG59
Female BNC - Twist on RG 6U
TN-5030RG6



Female BNC - Crimp on with 3 Ferrell's
(RG 58, RG-59, RG6U)
TN-5036



BNC male to RCA Male
TN5055



BNC female to RCA Male
TN-5071



The Best Guarantee Since 1984 : \$50-1

TANE ALARM PRODUCTS

906 JERICHO TURNPIKE, NEW HYDE PARK, NY 11040

Tel: 800-852-5050 • 516-328-3351 • Fax: 516-326-9125

www.tanealarm.com • E-MAIL: info@tanealarm.com